

SATURN 1000F2 (S1F2)

Installation Guide

Support Information

Contact the Yorkshire Payments Office

info@yorkshirepayments.com


01422 323785

Supervisor Password

0000

For a full user guide please visit -
www.yorkshirepayments.com

1. Your Terminal



2. Starting Up Your Terminal



Press and hold the power button (on the left side of the terminal) until the screen lights up.
The terminal will power on and initialise for use. When the 'Enter amount' message is displayed, the terminal is ready to use!

SATURN 1000F2 (S1F2)

Installation Guide

3. Terminal Interface

Till Roll
Compartment

Card Reader
(Contactless)

5.5" LCD Display

Insert card for
Chip & Pin



4. Charging Options

Option 1 - Charge With Cable

Connect the power supply to the port with a lightning symbol.
Connect the other end to the power outlet.

Option 2 - Charge With Base

Connect the 'USB type C' cable to the terminal port with the USB symbol.
Connect the other end of the cable into the USB power plug, into an electrical outlet.



5. Clearing Screensaver

To clear the Yorkshire Payments screensaver, please tap the screen.


The screen may enter power saving mode, in this case the screen turns dark. To wake up your terminal tap the power button (do not hold).

SATURN 1000F2 (S1F2)

Installation Guide

6. Setting Up WiFi

- Press on MENU icon, then press the black arrow from the bottom of the screen, then click on Wi-Fi setting icon.
- The terminal will display a list of the available networks, select the one you wish to connect to by clicking on it, the terminal will prompt to type in the password. Click on the horizontal line to open the keyboard. Key in the password as required.
- Once password entered press CONNECT; once successfully connected, the terminal will display message 'STATE CONNECTED'
- Click on the back-arrow from the top left side of the screen to return to Enter amount screen.



Once password entered press **CONNECT**; once successfully connected, the terminal will display message State: **CONNECTED**

8. Setting Up GPRS

Turn off the 'USE WIFI' toggle, the device will roam through the best available networks and auto select.




SATURN 1000F2 (S1 F2)

Installation Guide

9. Switch Network Type

- Follow the steps for setting up your Wi-Fi
- Select the network you want to switch to
- Enter the Wi-Fi password and press **CONNECT**



ACQUIRER (Bank)

- No funds are coming to my business account
- There is a discrepancy between funds I have received and what I was expecting I need to change my bank details

Yorkshire Payments

- Order new or additional equipment
- Add/remove functionality on the terminal
- Questions about contract (fees, charges, length, etc.)
- Update your details (address, contact, etc.)
- Training (how to use the terminal)
- Technical issues (terminal is not functioning properly)
- Tracking and delivery queries